

## Sinclair QL ROM switcher ver. 2

Pages	ROM switcher address range		QL address range	ROM images	SW1	SW2	SW3	SW4
Page 0	00000h - 0FFFFh	00000h - 0BFFFh	00000h - 0BFFFh	JM ROM	On	On	On	On - Toolkit 2 enable
		0C000h - 0FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 1	10000h - 1FFFFh	10000h - 1BFFFh	00000h - 0BFFFh	JS ROM	Off	On	On	On - Toolkit 2 enable
		1C000h - 1FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 2	20000h - 2FFFFh	20000h - 2BFFFh	00000h - 0BFFFh	MG ROM	On	Off	On	On - Toolkit 2 enable
		2C000h - 2FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 3	30000h - 3FFFFh	30000h - 3BFFFh	00000h - 0BFFFh	Spanish MG ROM	Off	Off	On	On - Toolkit 2 enable
		3C000h - 3FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 4	40000h - 4FFFFh	40000h - 4BFFFh	00000h - 0BFFFh	French MG ROM	On	On	Off	On - Toolkit 2 enable
		4C000h - 4FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 5	50000h - 5FFFFh	50000h - 5BFFFh	00000h - 0BFFFh	German MG ROM	Off	On	Off	On - Toolkit 2 enable
		5C000h - 5FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 6	60000h - 6FFFFh	60000h - 6BFFFh	00000h - 0BFFFh	Italian MG ROM	On	Off	Off	On - Toolkit 2 enable
		6C000h - 6FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable
Page 7	70000h - 7FFFFh	70000h - 7BFFFh	00000h - 0BFFFh	Minerva 1.98	Off	Off	Off	On - Toolkit 2 enable
		7C000h - 7FFFFH	0C000h - 0FFFFH	Toolkit 2 ver. 2.23				Off - Toolkit 2 disable

**For burning via EEPROM programmer all switches ( SW1 - SW4 ) should be in Off position.**

**If you connect external switch all internal switches should be in Off position.**